

Single Loop Panel



Features:

- Single Loop, supporting Apollo (Discovery, Xplorer, S90 & XP95) and Hochiki ESP protocols.
- Advanced graphical LCD user interface with up to 250 fire zones as standard, allowing full EN54 compliance without additional hardware or LED indication.
- Integral power supply and charger to EN54 part 4.
- Dedicated RS232 serial port for direct PC, modem or external printer connection.
- Dual, flash based, microprocessor technology with on-board Real Time Clock.
- Installer friendly 'Auto-learn' facility for uncomplicated, trouble-free, commissioning and fault finding.
- Fully on-site programmable via on-board alphanumeric keypad or PC configuration tools.
- Dedicated system and navigation keys for simple user control.
- User-friendly Windows based *PC-Net* configuration software includes virtual panel for remote diagnostics functionality via a low cost modem connection.
- Common integral loop driver can be configured for Apollo or Hochiki protocols.
- 500mA available loop current for connection of loop driven sounders and other field devices.
- Powerful cause and effect programming coupled with the flexible 'Dynamix' zoning makes the panel suitable for a wide range of site applications including the most complex multi area systems.
- Programmable variable sensitivity (Day/Night) modes with multiple 7-day timers.
- Robust, removable equipment chassis with plug-in connectors for simple fixing and cable termination
- The panel supports (protocol dependant) automatic Contamination warning, Sensitivity Band selection and Rapid Drift Compensation.
- When connected to the fault tolerant *Ad-Net* network, the panel operates as a true peer-to-peer interface (with up to 250 shared zones) with full cross panel reporting, control and cause and effect functionality.
- Flash memory and the advanced graphical display enables the panels to be configured to operate in virtually any language with any character set and allows the installer's logo and company details to be applied to the LCD display.
- The powerful 'Trace' diagnostics feature enables highly accurate device monitoring with event tracing and load monitoring of all loop, sounder and auxiliary outputs
- Optional LED expander board.



Sales Order Parts:	Options:	
Mx-4100: Single Loop Analogue Addressable Mx-4100/L: 1 Loop Analogue Addressable c/w Lockable Hinged Door Mx-4100/LG: 1 Loop Analogue Addressable c/w Lockable Hinged Door & Perspex Kit	Mxp-024F: 20 Zone LED Card Mxp-011: Access enable key switch Mxp-003: Standard Network card Mxp-009: Fault Tolerant Network card	Mxm-001: Semi-Flushing bezel

Mx-4100	Specification Details
Base Technology	Dual Flash based Processors with real time clock, 'TracE' diagnostics, 'PuLsE' communications & programmable languages
Display	Backlit 240x64 Graphical LCD
LED Indicators	3 Red (2 x Fire, 1 x Alarm), 1 Green (Power) & 12 Amber (Fault & System)
Controls	Alpha Numeric Keypad, Navigation Keys & System Keys for Reset, Mute, Silence/Resound & Evacuate
Protocols	Hochiki ESP, Apollo XP95, S90, Xplorer and Discovery
Number of Fire Zones	250 'Dynamix' when networked (100 per individual panel)
Number of Loops	1
Devices per loop	As per Detector Manufacturer's Specifications
Loop Current	500mA
On Board Sounder circuits	2 x 1 Amp Programmable
On Board Relays	2 x 1 Amp 30v AC/DC Programmable
Auxiliary Supply	1 x 24v 300mA (500mA from S/W V019)
Open Collector / Logic Outputs	2 x Programmable (via optional 2-way relay card)
Programmable Switch Inputs	8 x Volt Free Digital Inputs (via optional 8-way input card on Mx-4100/L)
Total Available Output Current	2 Amps maximum available for loop current + sounder outputs + auxiliary supply
Mains Supply	230 V (+10%, -15% tolerance) 50/60Hz AC 0.4 Amp maximum
Battery Capacity	24v 4 Ah internal minimum. 24v 7Ah maximum (Mx-4100), 24v 12Ah maximum (Mx-4100/L)
Charger Current	0.4 Amp DDP monitored, temperature compensated integral charger
Serial ports	1 x RS232 Onboard for PC, Modem or External Printer
Programming	Via on-board Keypad or PC running Windows Tools
Event Log	1000 Fire & Event + Diagnostic
Networking	Optional plug in Network card
Printer (Option)	External Serial Printer
Enclosure / Colour	Steel IP30 / Beige (textured)
Cable Entry	20mm Knock-outs. 7 x top, 7 x top rear
Size H x W x D mm	Enclosure Mx-4100: 320 x 345 x 88, Back Box only (When recessing): 320 x 345 x 70 Enclosure Mx-4100/L: 320 x 345 x 125
Weight	Mx-4100: 5Kg, Mx-4100/L: 6kg
Metalwork Options	Semi Flushing Bezel, Lockable Enclosure and a range of special finishes including Stainless Steel, Brass and Chrome
Approvals	BS EN54-2:1998, BS EN 54-4:1998
As our policy is one of constant product improvement the right is therefore reserved to modify product specifications without prior notice	

Moorland House : Nelson Park : Cramlington
Northumberland : NE23 1WE
Tel: +44 (0)1670 707 111
Fax: +44 (0)1670 707 222
www.Advel.co.uk Email: Sales@Advel.co.uk



ISO9001



ISO9001